

Sprint 382



230V



Incorporated in Falcon M5 ENC, Falcon M8 C ENC, Falcon M14 C, Falcon M20 C, Blizzard 500 C ENC and Blizzard 900 C ENC gearmotors.

Code

202269

Power supply (Vac)	230 (+6% -10%) 50Hz
Absorbed power (W)	10
Motor load Max. (W)	1000
Max. accessories load (mA)	500
Operating temperature (°C)	-20 +55
Protection fuses	2
Operating logic	Automatic/Automatic "Step by Step"/Semi-automatic/Safety/ Semi-automatic B/Dead man C/Semi-automatic "Step by Step"
Work time	Programmable (from 0 to 4 minutes)
Pause time	Programmable (from 0 to 4 minutes)
Thrust force	Adjustable on 50 levels
Inputs in terminal board	Open/Partial open/Stop/Opening and closing safeties/Stop/ Safety edge/Power Supply + earth
Connector inputs	Opening and closing limit switches/Encoder
Outputs in terminal board	Flashing light/Motor/24 Vdc accessories power supply/Indicator light 24Vdc/Failsafe
Quick connector	Genius 5-PIN receivers
Programming	3 buttons (+, -, F) and display, simple or complete mode
Simple Mode programmable functions	Operating logics/Pause time/Thrust force/Gate direction
Complete Mode programmable functions	Torque at initial thrust/Braking/Failsafe/Pre-flashing/Indicator light/Safeties logic/Encoder/ Slowdowns/Partial opening time/Work time/Assistance request/Cycles counting

ACCESSORIES



Single channel receiver 433 JLC

Code 6100351

Two-channel receiver 868 JLC

Code 6100353

Plug-in receivers with 5-pin Molex connector compatible with Genius control boards with 5-pin connectors.

Single channel receiver 868 JLC

Code 6100352

Single channel receiver 433 RC

Code 6100354

Single channel receiver 433 RC

Code 6100355